

GASOLINE PORTABLE SERIES

ELECTRIC START ENGINE 3000 RPM

Air Cooled

3000 rpm



HONDA

AVR

AUTOMATIC VOLTAGE REGULATOR



	MGTP 11 H BM AE	MGTP 11 H BT AE AVR	MGTP 11 H BT AE
Code	PP66-11M00	PP68-11T00	PP67-11T00
On board control panel equipped with:			
	- Hour counter - Volt meter - Main circuit breaker - 1x32A 3ph 230V EEC socket - 1x16A 1ph 230V EEC socket	- Hour counter - Volt meter - Main circuit breaker - 1x32A 3ph 400V EEC socket - 1x16A 1ph 230V EEC socket	- Hour counter - Volt meter - Main circuit breaker - 1x32A 3ph 400V EEC socket - 1x16A 1ph 230V EEC socket
Generator			
Type	Linz E1C11MB	Linz E1X13SB c/w AVR	Linz E1S10LL
Power	11 kVA 230V	11 kVA 400V	11 kVA 400V
Frequency	50 Hz	50 Hz	50 Hz
Engine			
	HONDA	HONDA	HONDA
Engine type	GX630	GX630	GX630
N° cylinders	2	2	2
Power	20,8 HP	20,8 HP	20,8 HP
Engine speed	3000 r.p.m.	3000 r.p.m.	3000 r.p.m.
Cooling	Air	Air	Air
Fuel	Unleaded gasoline	Unleaded gasoline	Unleaded gasoline
Starting system	Electric	Electric	Electric
Dimensions & weight			
Fuel tank capacity	13,3 lt	13,3 lt	13,3 lt
Running Time	2,8 hrs	2,8 hrs	2,8 hrs
Dry weight	123 Kg	130 Kg	130 Kg
Dimensions (L. x W. x H.)	780 x 520 x 750 mm	780 x 520 x 750 mm	780 x 520 x 750 mm

Options

- Site tow trailer
- Road tow trailer
- Trolley

Legend

Gasoline	Single phase	Air cooled
Diesel	Three phase	Water cooled

TEKNO PROGET
Generators & Welders

27030 Villanova D'Ardenghi (PV) Italy • Via Roma 6
Tel. +39 02 942 1464 - Sales Dept. +39 0382 406 252

www.teknoproget.com
info@teknoproget.com

The company reserves the right to modify the technical specifications, items and design without notice. The images of the products are indicative for illustrative purposes only.