

GASOLINE PORTABLE SERIES

MANUAL START ENGINE 3000 RPM

Air Cooled

3000 rpm

LWA
2000/14/CE

HONDA

AVR
AUTOMATIC
VOLTAGE
REGULATOR



G S A

G S A

G S A

	MGTP 3,5 H BM AS	MGTP 4,8 H BM AS AVR	MGTP 4,8 H BM AS
Code	PP58-4MO0	PP60-5MO0	PP59-5MO0
On board control panel equipped with:	- Hour counter - Volt meter - Main circuit breaker - 1x16A 1ph 230V EEC socket - 1x16A 1ph 230V Schucko socket	- Hour counter - Volt meter - Main circuit breaker - 1x16A 1ph 230V EEC socket - 1x16A 1ph 230V Schucko socket	- Hour counter - Volt meter - Main circuit breaker - 1x16A 1ph 230V EEC socket - 1x16A 1ph 230V Schucko socket
Generator			
Type	Linz E1C10SD	Linz E1C10SF c/w AVR	Linz E1E10MH
Power	3,5 kVA 230V	4,8 kVA 230V	4,8 kVA 230V
Frequency	50 Hz	50 Hz	50 Hz
Engine	HONDA	HONDA	HONDA
Engine type	GX160	GX270	GX270
N° cylinders	1	1	1
Power	4,8 HP	8,4 HP	8,4 HP
Engine speed	3000 r.p.m.	3000 r.p.m.	3000 r.p.m.
Cooling	Air	Air	Air
Fuel	Unleaded gasoline	Unleaded gasoline	Unleaded gasoline
Starting system	Manual recoil	Manual recoil	Manual recoil
Dimensions & weight			
Fuel tank capacity	3,1 lt	5,3 lt	5,3 lt
Running Time	2,8 hrs	2,7 hrs	2,7 hrs
Dry weight	47 Kg	71 Kg	71 Kg
Dimensions (L. x W. x H.)	620 x 440 x 540 mm	760 x 520 x 620 mm	760 x 520 x 620 mm

Options

- ⊙ Site tow trailer
- ≡⊙ Road tow trailer
- ⊙ Trolley

Legend

G	Gasoline	S	Single phase	A	Air cooled
D	Diesel	T	Three phase	W	Water cooled

TEKNO PROGET
Generators & Welders

27030 Villanova D'Ardenghi (PV) Italy • Via Roma 6
Tel. +39 02 942 1464 - Sales Dept. +39 0382 406 252

www.teknoproget.com
info@teknoproget.com

The company reserves the right to modify the technical specifications, items and design without notice. The images of the products are indicative for illustrative purposes only.